



15W / 30W COB LED PORTABLE FLOODLIGHT AND POWERBANK

MODEL NO: **LED1500PB (15W), LED3000PB (30W)**

Thank you for purchasing a Sealey product. Manufactured to a high standard, this product will, if used according to these instructions, and properly maintained, give you years of trouble free performance.

IMPORTANT: PLEASE READ THESE INSTRUCTIONS CAREFULLY. NOTE THE SAFE OPERATIONAL REQUIREMENTS, WARNINGS & CAUTIONS. USE THE PRODUCT CORRECTLY AND WITH CARE FOR THE PURPOSE FOR WHICH IT IS INTENDED. FAILURE TO DO SO MAY CAUSE DAMAGE AND/OR PERSONAL INJURY AND WILL INVALIDATE THE WARRANTY. KEEP THESE INSTRUCTIONS SAFE FOR FUTURE USE.



Refer to instructions

1. SAFETY

1.1. GENERAL

- ✓ Ensure the lamp is fully charged before initial use.
- ✗ **DO NOT** turn the lamp on when it is being charged.
- ✗ **DO NOT** shine directly into your, other person's or an animal's eyes.
- ✗ **DO NOT** allow children to use the lamp.
- ✗ **DO NOT** handle or move the lamp whilst it is being charged.
- ✗ **DO NOT** use the lamp if you suspect that the battery, the lamp casing or the cable is damaged. Consult your Sealey Stockist.
- ✗ **DO NOT leave battery in a discharged state, recharge battery immediately. Before storage, fully recharge the battery, subsequently recharge the battery at least once every six months of non-use.**

1.2. BATTERY SAFETY

- WARNING!** To reduce the risk of burns or fire:
 - ✗ **DO NOT** Attempt to open, dismantle, modify or service the battery pack.
 - ✗ **DO NOT** Crush, puncture, short external contacts or dispose of in fire or water.
 - ✗ **DO NOT** Expose to temperatures above 40°C or below -10°C.
 - ✗ **DO NOT** Expose to direct sunlight for long periods of time.
 - ✗ **DO NOT** Expose to moisture.
- WARNING! DO NOT** place the lamp face down while in use.
- ✓ Replace only with the battery pack designated for this product.
- ✓ Recycle or dispose of used battery as stipulated by local regulation.
- ✓ If the electrolyte in the cells gets on your skin, wash thoroughly with soap and water. If it gets in your eyes, rinse thoroughly with cool water and seek immediate medical attention.

2. INTRODUCTION

LED1500PB (15W COB LED)

15W COB LED Compact portable floodlight. Five modes of light ranging from 150-1500 lm. Rechargeable high quality 3.7V Li-ion battery. 180° swivel stand for a range of lighting angles. Five LED Battery level indicators and low power warning. Supplied with 1m Type-C USB Charging cable. Powerbank output 5V-2A.

LED3000PB (30W COB LED)

30W COB LED Compact portable floodlight. Five modes of light ranging from 300-3000lm. Rechargeable high quality 7.4V Li-ion battery. 180° swivel stand for a range of lighting angles. Five LED Battery level indicators and low power warning. Supplied with 1m Type-C USB Charging cable. Powerbank output 5V-2A.

3. SPECIFICATION

Model No.:..... **LED1500PB**
Battery: 3.7v 5200mAh Li-ion
Charging Time: 3.5 hours
IP Rating: IP65
LED Type: COB LED
Lumen Output:
 Mode 1- 150 lumen
 Mode 2- 375 lumen
 Mode 3- 750 lumen
 Mode 4- 1125 lumen
 Mode 5- 1500 lumen
USB Output:..... 5V 2A
Operating time:
 Mode 1- 25 hour, Mode 2- 12 hour, Mode 3- 6 hour
 Mode 4- 4 hour, Mode 5- 3 hour
Power:.....15W

Model No.:..... **LED3000PB**
Battery:7.4V 5200mAh Li-ion
Charging Time: 5.5 hours
IP Rating:IP65
LED Type: COB LED
Lumen Output:
 Mode 1- 300 lumen
 Mode 2- 750 lumen
 Mode 3- 1500 lumen
 Mode 4- 2250 lumen
 Mode 5- 3000 lumen
USB Output:..... 5V 2A
Operating time:
 Mode 1- 25 hour, Mode 2- 12 hour, Mode 3- 6 hour
 Mode 4- 4 hour, Mode 5- 3 hour
Power:.....30W

The battery fitted to this lamp is considered to be a consumable item and its ability to accept a charge will reduce over time. We will provide warranty against mechanical and electrical defect for a period of one year - this does not cover fair wear and tear. If the battery is not properly charged before first use, or regularly conditioned, its capacity will diminish. Under these circumstances we will not replace the battery regardless of whether it is less than one year old.
NOTE: The lithium battery does not suffer from memory effect and once fully charged may be stored for up to six months without another charge.

4. OPERATION

4.1. CHARGING

4.1.1. Insert the Micro USB plug on the USB cable into the charging port on the rear of the lamp.

4.1.2. Plug the other end of the USB cable into a 5V USB outlet.

☐ **WARNING! DO NOT** turn lamp on whilst charging.

4.1.3. The battery indicator will blink red during charging.

4.1.4. When the battery has charged fully, the battery indicator will glow green.

4.2. USE OF LAMP

4.2.1. Direct the lens away from your eyes, other people and animals before switching on.

4.2.2. Push the ON/OFF switch once for FULL power mode, twice for HALF power mode and a third time for flashing mode.

IMPORTANT: Only use the cable supplied with the product.

4.3. POWER BANK

4.3.1. Insert the USB plug from the remote device into the charging port on the rear of the lamp. The LED on the lamp will be lit green while charging the remote device.

5. MAINTENANCE

5.1. Clean the casing externally (not the glass) with a moist cloth.

5.2. If necessary clean the glass with an alcohol dampened soft cloth.

× **DO NOT** use solvents or abrasives.

× **DO NOT** allow unit to get wet or use/store in a damp environment.



ENVIRONMENT PROTECTION

Recycle unwanted materials instead of disposing of them as waste. All tools, accessories and packaging should be sorted, taken to a recycling centre and disposed of in a manner which is compatible with the environment. When the product becomes completely unserviceable and requires disposal, drain any fluids (if applicable) into approved containers and dispose of the product and fluids according to local regulations.



WEEE REGULATIONS

Dispose of this product at the end of its working life in compliance with the EU Directive on Waste Electrical and Electronic Equipment (WEEE). When the product is no longer required, it must be disposed of in an environmentally protective way. Contact your local solid waste authority for recycling information.



BATTERY REMOVAL

Under the Waste Batteries and Accumulators Regulations 2009, Jack Sealey Ltd are required to inform potential purchasers of products containing batteries (as defined within these regulations), that they are registered with Valpak's registered compliance scheme. Jack Sealey Ltd's Batteries Producer Registration Number (BPRN) is BPRN00705.

Note: It is our policy to continually improve products and as such we reserve the right to alter data, specifications and component parts without prior notice.

Important: No Liability is accepted for incorrect use of this product.

Warranty: Guarantee is 12 months from purchase date, proof of which is required for any claim.

Sealey Group, Kempson Way, Suffolk Business Park, Bury St Edmunds, Suffolk. IP32 7AR



01284 757500



01284 703534



sales@sealey.co.uk



www.sealey.co.uk